

Table 2. Special Lynx Earthing Nut Specifications for use on single cables with protective conductors sized to BS7671 Table 54G

Lynx stock Code	Thread size mm	Connection hole size	Conductor size sq mm	Protective Conductor sq mm	Kompress Terminal	Takbro Terminal	Davico-Krimpit Terminal	SWA Terminal TQ Range	Hexagon size mm	Nut thickness mm	Number of teeth	Connecting screw style.	
PEN 25S	25	M10	50	25	CT25-10	TU25-10	D25-10	HD25-10	45	20	6	BZP Stud+Nut	
PEN 25S	25	M10	70	35	CT35-10	TU35-10	D35-10	HD35-10	45	20	6	BZP Stud+Nut	
PEN 25S	25	M10	95	50	CT50-10	TU50-10	D50-10	HD50-10	45	20	6	BZP Stud+Nut	
PEN 32S	32	M10	120	70	CT70-10	TU95-10	D70-10	HD70-10	51	25	6	BZP Stud+Nut	
PEN 32S	32	M10	150	95	CT95-10	TU95-10	D95-10*	HD95-10	51	25	6	BZP Stud+Nut	
PEN 32S	32	M10	185	95	CT95-10	TU95-10	D95-10*	HD95-10	51	25	6	BZP Stud+Nut	
PEN 40S	40	M12	240	120	CT120-12	TU120-12*	D120-12	HD120-12	66	31	6	BZP Stud+Nut	
PEN 40S	40	M12	300	150	CT150-12	TU150-12*	D150-12*	HD150-12*	66	31	6	BZP Stud+Nut	
PEN 50S	50	M16	400	240	CT240-16	TU240-16	D240-16	HD240-16	80	44	6	BZP Stud+Nut	
PEN 50S	50	M16	500	300	CT300-16	TU300-16	D300-16	HD300-16	80	44	6	BZP Stud+Nut	
Special order only. Conductor size for guidance only. Nut should be sized to fit gland which is the closest fit to the size of cable being used.					*Cannot be fitted parallel with conductors.								With BZP Washer